

der K1520-Bus

Vergleich der Belegungen des Bus-Steckverbinders verschiedener DDR-Computer.

| KC85 K1520 | K1520 KC85 | BIC | Z1013 | Z1013 | KC87 | A-B/C | KC87 | Z1013 | BIC | |
|---------------|---------------|--------|--------|--------|--------|-------|--------|--------|--------|-------|
| 00 | 00 | 00 | 00 | 00 | 1 | 00 | 00 | 00 | 00 | 00 |
| 00 | 00 | 00 | 00 | 00 | 2 | 00 | 00 | 00 | 00 | 00 |
| n.c. | 5PG | 12N | 12N | 12N | 3 | 12N | 12N | 5PG | n.c. | |
| DB7 | DB7 | DB7 | DB7 | DB7 | 4 | DB6 | DB6 | DB6 | DB6 | DB6 |
| DB5 | DB5 | DB5 | DB5 | DB5 | 5 | DB4 | DB4 | DB4 | DB4 | DB4 |
| DB3 | DB3 | DB3 | DB3 | DB3 | 6 | DB2 | DB2 | DB2 | DB2 | DB2 |
| DB1 | DB1 | DB1 | DB1 | DB1 | 7 | DB0 | DB0 | DB0 | DB0 | DB0 |
| /WR | /WR | /WR | /WR | /WR | 8 | /RD | /RD | /RD | /RD | /RD |
| /MREQ | /MREQ | /MREQ | /MREQ | /MREQ | /MREQ | 9 | /ROMDI | /MEMDI | /ROMDI | |
| /MEMDI | /IORQ | | | | | | | | | |
| IE0 | /IE0 | /IE0 | /IE0 | /IE0 | 10 | n.c. | /IORQ1 | /IEI | /IEI | |
| n.c. | | | | | | | | | | |
| AB14 | AB14 | AB14 | AB14 | AB14 | 11 | AB15 | AB15 | AB15 | AB15 | AB15 |
| AB15 | | | | | | | | | | |
| AB12 | AB12 | AB12 | AB12 | AB12 | 12 | AB13 | AB13 | AB13 | AB13 | AB13 |
| AB13 | | | | | | | | | | |
| AB10 | AB10 | AB10 | AB10 | AB10 | 13 | AB11 | AB11 | AB11 | AB11 | AB11 |
| AB11 | | | | | | | | | | |
| AB08 | AB08 | AB08 | AB08 | AB08 | 14 | AB09 | AB09 | AB09 | AB09 | AB09 |
| AB09 | | | | | | | | | | |
| /WAIT | 5N | n.c. | 5N | 5N | 15 | 5N | 5N | n.c. | 5N | /RFSH |
| AB06 | AB06 | AB06 | AB06 | AB06 | 16 | AB07 | AB07 | AB07 | AB07 | AB07 |
| AB07 | | | | | | | | | | |
| AB04 | AB04 | AB04 | AB04 | AB04 | 17 | AB05 | AB05 | AB05 | AB05 | AB05 |
| AB05 | | | | | | | | | | |
| AB02 | AB02 | AB02 | AB02 | AB02 | 18 | AB03 | AB03 | AB03 | AB03 | AB03 |
| AB03 | | | | | | | | | | |
| AB00 | AB00 | AB00 | AB00 | AB00 | 19 | AB01 | AB01 | AB01 | AB01 | AB01 |
| AB01 | | | | | | | | | | |
| /RESET | /RESET | /RESET | /RESET | /RESET | /RESET | 20 | /BUSRQ | /BUSRQ | /BUSRQ | |
| /BUSRQ | /BUSRQ | /BUSRQ | /BUSRQ | /BUSRQ | | | | | | |
| TAKT | TAKT | TAKT | TAKT | TAKT | 21 | 00 | 00 | 00 | 00 | 00 |
| /M1 | /IODI | /SL3 | /IODI | ETR | 22 | 00 | 00 | 00 | 0 | /HALT |
| /NMI | /NMI | /NMI | /NMI | /NMI | 23 | /INT | /INT | /INT | /INT | /INT |
| /INT | | | | | | | | | | |
| ME0 | /WAIT | /WAIT | /WAIT | /WAIT | 24 | /IORQ | /IORQ | /IORQ | /IORQ | |
| /IORQ | MEI | | | | | | | | | |
| /ZI | /RFSH | /RFSH | /RFSH | /RFSH | 25 | CASG | /CASG | n.c. | /RDY | |
| /BI | | | | | | | | | | |
| n.c. | /M1 | /M1 | /PM1 | /M1 | 26 | /HALT | /HALT | /HALT | /HALT | /HALT |
| /HELL | | | | | | | | | | |

| | | | | | | | | | |
|--------|------|------|--------|------|----|------|------|------|------|
| /BUSAK | /BA0 | /BAI | /BUSAK | /BA0 | 27 | n.c. | n.c. | /BA0 | /BAI |
| n.c. | | | | | | | | | |
| 12P | 12P | 12P | 12P | 12P | 28 | 12P | 12P | 12P | n.c. |
| n.c. | 5P | 5P | 5P | 5P | 29 | 5P | 5P | 5P | n.c. |

From:
<https://hc-ddr.hucki.net/wiki/> - **Homecomputer DDR**

Permanent link:
<https://hc-ddr.hucki.net/wiki/doku.php/homecomputer/k1520?rev=1427184821>

Last update: **2015/03/24 08:13**

